Australia / NZ Partners | Where To Buy





PRODUCT NUMBER: 2091911 ELECTROSOFT CLASS 1

For electrical work with a maximal voltage of 7500 volts. To be used with leather protectors for mechanical protection.

Honeywell

Overview

Reference Number

2091911

Product Type

Gloves

Range

Electrical Protection

Line

Latex

Brand

Honeywell

Brand formerly known as

ELECTROSOFT

Industry

• Energy or Electricity • Maintenance • Telecoms

Product Use

For electrical work with a maximal voltage of 7500 volts. To be used with leather protectors for mechanical protection.

Features & Benefits

Feature

Beige natural latex insulating glove Cut edge

Category RC

Benefit

COMFORT

Its ergonomic design combined with a lightly powdered interior increases the comfort by providing additional softness and allows the glove to be put on and taken off very easily.

RESISTANCE

The natural latex base offers high dielectric characteristics.

Its thickness (1.5mm) provides good dexterity while offering protection up to 7,500 volts.

ELECTROSOFT CLASS 1 - 2091911

SAFETY

His length protects a large part of the forearm.

To be used with leather protectors for mechanical protection.

Technical Description

Description

CE CATEGORY : III Irreversible risks In accordance with standards :

EN 60903-2003 CEI 903-2002

CHARACTERISTICS:

Beige natural latex insulating glove

Cut edge Category RC

Product Technology

Dipped Gloves

Glove/liner color

Beige

Coating Type

Latex

Length

41 cm

Thickness

1.5 mm

Harmlessness

In conformity with the European standards

Dexterity

Class 1

Sizes

8 to 11

Packaging Label

Tagging

CE HONEYWELL 2091911 XX EN 60903-2003 CEI 903-2002

Certifications

EU Category PPE

3

Quality Assurance

ISO 9001 / 2000

EU Certification

EU Attestation

Additional Information

User Information Sheet

On the polybag

ELECTROSOFT CLASS 1 - 2091911

Maintenance

Life Cycle

Gloves that are used frequently should be tested at intervals less than 6 month.

Gloves that are used only occasionally should be tested after each use and, in any case, at intervals of not more than 12 months

Gloves held in stock should be retested at intervals not exceeding 12 months.

Storage Information

Store in original packaging (Opaque and anti-UV packaging used for protection and instructions for use). Do not compact or fold.

Do not expose to heat sources (sunlight, radiators, artificial light). Store between 10°C and 21°C.

Care Instructions

Inspection:

Before each use, carry out a visual inspection and check the glove inflation. Any puncture or perforation makes the gloves unusable.

Precautions:

Do not expose to solvents or chemicals that may cause deterioration. Do not use the glove when damp.

Cleaning:

Use water and soap. Dry below 65°C with ambient humidity.

D Honeywell International Inc.